

Loading Plotter driver from HP Website

Downloading from HP Website

- Download plotter driver from www.hp.com
- Click on **SUPPORT & DRIVERS**
- Select **DOWNLOAD DRIVERS and SOFTWARE**
- Click on box next to **For:**, Type **750C** (HP750C is a common plotter), **ENTER**
- Click on **HP DESIGNJET 750C PRINTER (E/AO-SIZE)**
- Under **Full Product Index**, Click on **750C**
- Under **Downloads**, Click on **DRIVERS & DOWNLOADS**
- Click on **SKIP REGISTRATION**
- Select your **operating systems**
- Scroll down to: **DRIVER**, Select **DOWNLOAD**
- Select **SAVE** (save this on your Desktop or hard drive)
- Click on **SAVE**
- When Complete, Click on **Close**

How to Unzip Downloaded File

- Locate the downloaded file, double left click on **FILE**
- Select **BROWSE** to extract your file to a folder on your hard drive
- Select **UNZIP**
- When self-extractor is complete, click on **O.K.**
- Close Dialog Box

Loading Print Driver

- Click on **Start Menu** (lower left corner of your screen)
- Go to **Settings**
- Click on **PRINTERS**
- Double click on **ADD PRINTER**
- Click **NEXT** in the **Add Printer Wizard dialog box**
- Select **Local Printer**, click **NEXT** and **NEXT**
- In **Add Printer Wizard**, select **HAVE DISK**
- Select **BROWSE** (locate unzipped file)
- Select **OEMSETUP.INF** file, then Select **OPEN**
- Select **O.K.**
- In **Add Printer Wizard Dialog Box**, **SELECT A PRINTER** (most common printer is HP DesignJet 750C (E/AO) by HP), select **NEXT**
- Name the printer **“CADD/Engineering Supply”** or another name that will let you know this is a **Plot-To-File printer only**, select **NEXT**
- Select **NO** for **default printer**, select **NEXT**
- Select **NO** for **“Do you want to print a test page”** – Remember this is a ghost plotter. It will not interfere with any physical plotter you have, Select **NEXT**
- Select **FINISH**

